


Main switch boxes



NXT HS-H6 hoofdschakelaarkast

| | |
|--|--|
| Article no: | AT91021 |
| EAN: | 8712259533919 |
| Width | 220 mm |
| Height | 190 mm |
| Rated current | 63 A |
| Phases | 3-phase wired |
| Main switch | 63 A |
| Connecting wires | Yes |
| Quantity and type of FI/LS switch | |
| Mounting method | Cabinet mounted/skeleton unit |
| Degree of protection (IP) | IP20 |
| Width in number of modular spacings | 12 |
| Depth | 110 mm |
| Extension possible | Yes |
| Housing material | Plastic |
| Number of phases | 3 |
| Lockable | Yes |
| Over voltage protection | No |
| Number of earth leakage switches 30 mA | |
| Number of earth leakage switches 300 mA | |
| With transparent cover | No |
| Protection | Miniature- / earth leakage circuit breaker |
| Total number of groups | |
| Number of direct groups | |
| Number of light groups | |
| Number of groups behind earth leakage switch | |
| Number of earth leakage circuit breakers | |
| Number of arc fault detection devices AFDD | |
| Protection main switch | No |
| Number of poles main switch | 4 |
| Main switch rated current | 63 A |
| Protection incoming RCD | No |
| Protection high integrity | No |
| Protection split load | No |
| Protection dual RCD | No |
| Number of outgoing ways | |
| Suitable for data | No |
| Cooker group | None |
| Cooker group suitable as power current group | No |
| With socket outlet | No |
| With bell transformer | No |
| Type of over voltage protection device | - |
| With meter | No |
| Built-in depth | 55 - 55 mm |

Main switch boxes without output bridge. Easy to install under the Click-mate NXT Distribution boxes or expansion boxes.