


Installation 2.0 Click-mate NXT distribution boards



NXT SAW-22/22-H2 groepenkast

| | |
|--|--|
| Article no: | AT91029 |
| EAN: | 8712259559605 |
| Width | 220 mm |
| Height | 250 mm |
| Number of groups (blue) | 2 |
| Number of groups (grey) | 2 |
| Number of earth fault switches 2P | 2 |
| Phases | 1-phase wired |
| Groups | 4 |
| Main switch | 40 A |
| Rated current | 40 A |
| Quantity and type of FI/LS switch | |
| Mounting method | Surface mounted (plaster) |
| Degree of protection (IP) | IP2XC |
| Width in number of modular spacings | 12 |
| Depth | 110 mm |
| Extension possible | Yes |
| Housing material | Plastic |
| Number of phases | 1 |
| Lockable | Yes |
| Over voltage protection | No |
| Number of earth leakage switches 30 mA | 2 |
| Number of earth leakage switches 300 mA | |
| With transparent cover | No |
| Protection | Miniature- / earth leakage circuit breaker |
| Total number of groups | 4 |
| Number of direct groups | |
| Number of light groups | 4 |
| Number of groups behind earth leakage switch | 4 |
| Number of earth leakage circuit breakers | |
| Number of arc fault detection devices AFDD | |
| Protection main switch | Yes |
| Number of poles main switch | 2 |
| Main switch rated current | 40 A |
| Protection incoming RCD | Yes |
| Protection high integrity | Yes |
| Protection split load | Yes |
| Protection dual RCD | Yes |
| Number of outgoing ways | |
| Suitable for data | Yes |
| Cooker group | None |
| Cooker group suitable as power current group | Yes |
| With socket outlet | No |
| With bell transformer | No |

| | |
|--|-----|
| Type of over voltage protection device | - |
| With meter | Yes |

Especially for the Installation 2.0 concept, Attema has extended its range of Click-mate NXT distribution boards with a pluggable output bridge. The fully pre-wired pluggable output bridge can be fitted with up to 12 to 16 connections for single-phase end groups. Connections for electric cooking, mechanical ventilation or power groups have also been taken into account: space is reserved in the output bridge for up to 2 to 4 pieces of 5-pin flat connectors. All connectors are pre-wired with 2.5 mm² and equipped with locking latches as standard.

Almost all "traditional" distribution boards can be equipped with a fully pre-wired output bridge with round connectors. Just like the standard distribution boards, Attema assembles the pluggable distribution boards completely as desired within a few days.

Looking for a different configuration? Use the Click-mate NXT Assistant tool to assemble your own pluggable distribution box in no time. Or ask one of our sales staff about the possibilities.