


## Distribution boxes with earth leakage switches and circuit breakers



## NXT L-24/23/23F/00-H4 groepenkast

<b>Article no:</b>	<b>AT92529</b>
EAN:	8712259535111
Width	330 mm
Height	390 mm
Number of groups (blue)	4
Number of groups (lightblue)	4
Number of groups (grey)	3
Number of earth fault switches 2P	3
Phases	3-phase wired
Groups	11
Cooking group	1-phase (F)
Main switch	40 A
Rated current	3 x 32 A
Quantity and type of FI/LS switch	
Mounting method	Surface mounted (plaster)
Degree of protection (IP)	IP20
Width in number of modular spacings	36
Depth	110 mm
Extension possible	Yes
Housing material	Plastic
Number of phases	3
Lockable	Yes
Over voltage protection	No
Number of earth leakage switches 30 mA	3
Number of earth leakage switches 300 mA	
With transparent cover	No
Protection	Miniature- / earth leakage circuit breaker
Total number of groups	11
Number of direct groups	
Number of light groups	10
Number of groups behind earth leakage switch	11
Number of earth leakage circuit breakers	
Number of arc fault detection devices AFDD	
Protection main switch	No
Number of poles main switch	4
Main switch rated current	40 A
Protection incoming RCD	No
Protection high integrity	No
Protection split load	No
Protection dual RCD	No
Number of outgoing ways	28
Suitable for data	No
Cooker group	Single phase
Cooker group suitable as power current group	No

With socket outlet	No
With bell transformer	No
Type of over voltage protection device	-
With meter	No
Built-in depth	55 mm

The new generation of Click-mate NXT distribution boxes is available in various editions: The compact S distribution cabinet with 12 modules, the familiar M distribution cabinet with space for 2 x 12 modules and the innovative L distribution cabinet with 2 x 18 modules; the solution for the energy transition and extensive 3-phase installations. The distribution boxes are also completely modular and can easily be installed next to or underneath each other. The distribution boxes in the extensive range are equipped with earth leakage circuit breakers (2P, 40A, 30mA) and circuit breakers (1P+N, 16A, B-characteristic) and are optionally available with a stove group and/or bell transformer.