## **Installation 2.0 Click-mate NXT distribution boards**



## NXT MAW-23/23/22-H4 groepenkast

EAN: 8712259559681	
VA!' 1d	
Width 220 mm	
Height 390 mm	
Number of groups (blue) 3	
Number of groups (lightblue) 2	
Number of groups (grey) 3	
Number of earth fault switches 2P 3	
Phases 3-phase wired	
Groups 8	
Main switch 40 A	
Rated current 3 x 32 A	
Quantity and type of FI/LS switch	
Mounting method Surface mounted (p	olaster)
Degree of protection (IP) IP2XC	
Width in number of modular spacings 24	
Depth 110 mm	
Extension possible Yes	
Housing material Plastic	
Number of phases 3	
Lockable Yes	
Over voltage protection No	
Number of earth leakage switches 30 mA 3	
Number of earth leakage switches 300 mA	
With transparent cover No	
Protection Miniature- / earth le	eakage circuit breaker
Total number of groups 8	
Number of direct groups	
Number of light groups 8	
Number of groups behind earth leakage 8 switch	
Number of earth leakage circuit breakers	
Number of arc fault detection devices AFDD	
Protection main switch Yes	
Number of poles main switch 4	
Main switch rated current 40 A	
Protection incoming RCD Yes	
Protection high integrity Yes	
Protection split load Yes	
Protection dual RCD Yes	
Number of outgoing ways	
Suitable for data Yes	
Cooker group None	
Cooker group suitable as power current group Yes	
With socket outlet No	



With bell transformer	No
Type of over voltage protection device	-
With meter	Yes

Especially for the Installation 2.0 concept, Attema has extended its range of Click-mate NXT distribution boards with a pluggable output bridge. The fully pre-wired pluggable output bridge can be fitted with up to 12 to 16 connections for single-phase end groups. Connections for electric cooking, mechanical ventilation or power groups have also been taken into account: space is reserved in the output bridge for up to 2 to 4 pieces of 5-pin flat connectors. All connectors are pre-wired with 2.5 mm² and equipped with locking latches as standard.

Almost all "traditional" distribution boards can be equipped with a fully pre-wired output bridge with round connectors. Just like the standard distribution boards, Attema assembles the pluggable distribution boards completely as desired within a few days.

Looking for a different configuration? Use the Click-mate NXT Assistant tool to assemble your own pluggable distribution box in no time. Or ask one of our sales staff about the possibilities.

