

## Installation 2.0 Click-mate NXT distribution boards



### NXT MAW-23/23/22F-H4 groepenkast

<b>Article no:</b>	<b>AT91627</b>
EAN:	8712259559698
Width	220 mm
Height	390 mm
Number of groups (blue)	3
Number of groups (lightblue)	3
Number of groups (grey)	3
Number of earth fault switches 2P	3
Phases	3-phase wired
Groups	9
Cooking group	3-phase (K)
Main switch	40 A
Rated current	3 x 32 A
Quantity and type of FI/LS switch	
Mounting method	Surface mounted (plaster)
Degree of protection (IP)	IP2XC
Width in number of modular spacings	24
Depth	110 mm
Extension possible	Yes
Housing material	Plastic
Number of phases	3
Lockable	Yes
Over voltage protection	No
Number of earth leakage switches 30 mA	3
Number of earth leakage switches 300 mA	
With transparent cover	No
Protection	Miniature- / earth leakage circuit breaker
Total number of groups	9
Number of direct groups	
Number of light groups	8
Number of groups behind earth leakage switch	8
Number of earth leakage circuit breakers	
Number of arc fault detection devices AFDD	
Protection main switch	Yes
Number of poles main switch	4
Main switch rated current	40 A
Protection incoming RCD	Yes
Protection high integrity	Yes
Protection split load	Yes
Protection dual RCD	Yes
Number of outgoing ways	
Suitable for data	Yes
Cooker group	Single phase
Cooker group suitable as power current group	No

With socket outlet	No
With bell transformer	No
Type of over voltage protection device	-
With meter	Yes

Especially for the Installation 2.0 concept, Attema has extended its range of Click-mate NXT distribution boards with a pluggable output bridge. The fully pre-wired pluggable output bridge can be fitted with up to 12 to 16 connections for single-phase end groups. Connections for electric cooking, mechanical ventilation or power groups have also been taken into account: space is reserved in the output bridge for up to 2 to 4 pieces of 5-pin flat connectors. All connectors are pre-wired with 2.5 mm<sup>2</sup> and equipped with locking latches as standard.

Almost all "traditional" distribution boards can be equipped with a fully pre-wired output bridge with round connectors. Just like the standard distribution boards, Attema assembles the pluggable distribution boards completely as desired within a few days.

Looking for a different configuration? Use the Click-mate NXT Assistant tool to assemble your own pluggable distribution box in no time. Or ask one of our sales staff about the possibilities.